



## T-MAG-SPT-300 Sensor

### 300 Volt AC Potential Transformer Sensor

The Magnelab 300-Volt AC Potential Transformer is used with the FlexSmart TRMS Module to provide accurate measurement of AC voltage. One or two PTs can be used with each FlexSmart TRMS module. This sensor offers an accuracy of  $\pm 1\%$  (from 10% to 130% of rated voltage), but because this transformers ties directly into the line, it should be used only by qualified personnel.



#### Supported Measurements:

AC Voltage

#### Key Advantages:

- 2 input channels of AC Current and/or Voltage
- Measures True RMS for accurate readings of sinusoidal and non-sinusoidal waveforms

## T-MAG-SPT-300 Sensor Specifications

**Measurement range:** 150, 300, 600 Volts AC  
**Accuracy:**  $\pm 1\%$  (from 10% to 130% of rated voltage)  
**Phase angle:**  $< 1$  degree  
**Output signal to FlexSmart Module:** 0.333 Volt at rated input voltage  
**Connections:** 8-ft PVC insulated wire, UL1015  
**High voltage input:** #14 AWG, blue/brown  
**Low voltage output:** #22 AWG twisted pair, black/white  
**Construction:** Epoxy filled ABS plastic  
**Dimensions:** 5.5 cm x 3.9 cm x 3.1 cm (2.2" x 1.6" x 1.2")  
**Weight:** 491.2g (17.33oz)  
**Number of data channels:** 1

To download the manual from Magnelab click [here](#).

## Contact Us

Sales (8am to 5pm ET, Monday through Friday)

- ▶ Email [sales@onsetcomp.com](mailto:sales@onsetcomp.com)
- ▶ Call 1-508-759-9500
- ▶ In U.S. toll free 1-800-564-4377
- ▶ Fax 1-508-759-9100

Technical Support (8am to 8pm ET, Monday through Friday)

- ▶ Contact Product Support [www.onsetcomp.com/support/contact](http://www.onsetcomp.com/support/contact)
- ▶ Call 1-508-759-9500
- ▶ In U.S. toll free 1-877-564-4377

Onset Computer Corporation  
470 MacArthur Boulevard  
Bourne, MA 02532